

# SET AUTO\_TIME

---

The SET AUTO\_TIME command controls how often *TCP/IP for VSE's* event processing (as enabled by the DEFINE EVENT command) scans the POWER queues looking for new work.

---

Syntax: SET AUTO\_TIME=30s

---

Arguments: *time* - Numeric, 1500 through 18000, in 300th seconds.

The amount of time between scans of the POWER queues by the *TCP/IP for VSE* event timer.

---

Example:

```
IPN237I set auto_time=1500
IPN268I AUTO_TIME now set to 1500 300th sec
```

- Notes:
- See the description of the DEFINE EVENT command for more information about *TCP/IP for VSE* event processing.
  - A large value saves CPU but makes *TCP/IP for VSE* take longer to detect new work on the Power queues. A small value uses additional CPU but makes event processing more responsive to new work.
- 

Related	DEFINE EVENT	- Monitor a POWER class for automatic report distribution.
Commands:	QUERY EVENTS	- Displays the status of automation processing.
	QUERY OPTIONS	- Displays the current values of modifiable parameters.

---